



Europäisches Patentamt
European Patent Office
Office européen des brevets



(11) EP 1 096 713 A2

(12) EUROPEAN PATENT APPLICATION

(43) Date of publication:
02.05.2001 Bulletin 2001/18

(51) Int Cl.7: H04J 14/02

(21) Application number: 00309452.1

(22) Date of filing: 26.10.2000

(84) Designated Contracting States:
AT BE CH CY DE DK ES FI FR GB GR IE IT LI LU
MC NL PT SE
Designated Extension States:
AL LT LV MK RO SI

(72) Inventors:
• Yoshizawa, Nobukazu
Minato-ku, Tokyo (JP)
• Iwano, Tadayuki, c/o NEC Corporation
Tokyo (JP)

(30) Priority: 26.10.1999 JP 30328099

(71) Applicant: NEC CORPORATION
Tokyo (JP)

(74) Representative: Moir, Michael Christopher et al
Mathys & Squire
100 Gray's Inn Road
London WC1X 8AL (GB)

(54) Optical add/drop multiplexer

(57) An optical add/drop multiplexer (OADM) is provided with an optical demultiplexer (ODMX), an optical coupler, a 2-input/1-output optical switch (2X1 SW) and an optical multiplexer (OMUX), respectively cascaded. The OADM demultiplexes a wavelength-multiplexed optical signal. The optical coupler branches a demultiplexed optical signal into first and second branched op-

tical signals. The second branched optical signal is a drop signal. The first branched optical signal and an add signal are incident on the 2X1 SW. When the add signal is output from the switch, the OMUX multiplexes the add signal and other optical signals, and outputs the result to an optical transmission line as a wavelength-multiplexed optical signal.




FIG.2A

EP 1 096 713 A2

Description

BACKGROUND OF THE INVENTION

1. Field of the Invention

[0001] The present invention relates to an optical add/drop multiplexer (hereinafter called OADM), and particularly relates to an optical add/drop multiplexer suitable for an optical communication system to which dense wavelength-division multiplex (hereinafter called D-WDM) is applied.

2. Description of the Related Prior Art

[0002] An optical communication system has been essential for the communication of multimedia information such as voice and an image. Particularly, a D-WDM system of multiplexing and transmitting plural optical signals different at a very short wavelength interval is suitable for a long distance/mass optical communication system. Normally, an OADM that extracts an optical signal of a specific wavelength (a specific channel) from a transmitted wavelength multiplexed optical signal or adds an optical signal of another specific wavelength to a wavelength multiplexed optical signal is installed at a repeater site of an optical transmission line for transmitting wavelength multiplexed optical signals. A well-known OADM of arbitrarily selective type is provided with an optical demultiplexer (hereinafter called ODMX), an optical multiplexer (hereinafter called OMUX) and 2-input/2-output optical switch (hereinafter called 2 x 2 SW) installed between these. A well-known arrayed waveguide grating (hereinafter called AWG) may be also used for ODMX and OMUX. AWG is plural parallel optical waveguides formed on a plane substrate for example, and each waveguide is arranged so that it is different from an adjacent waveguide in an optical path length by predetermined quantity. Therefore, AWG causes similar dispersion to a diffraction grating by a phase shift caused between each waveguide, and can demultiplex input wavelength-multiplexed light. An ODMX demultiplexes each optical signal from a wavelength-multiplexed optical signal, including plural optical signals having different wavelengths. A predetermined optical signal demultiplexed by ODMX is incident on a first input port of 2 x 2 SW. An add signal added to a wavelength multiplexed optical signal is incident on a second input port of 2 x 2 SW. A through signal (hereinafter a THR signal) multiplexed by OMUX is output from a first output port of 2 x 2 SW, and a drop signal extracted from a wavelength-multiplexed optical signal may be output from a second output port. 2 x 2 SW varies the intensity of the interference of optical signals input from two input terminals by applying heat, voltage or magnetism to an inside wavelength for transmitting an optical signal, and can apply polarity to these optical signals. Therefore, the input two optical signals are se-

lectively output from two output terminals. A THR signal output from 2 x 2 SW is incident on OMUX. OMUX multiplexes this THR signal and another optical signal demultiplexed by ODMX. In case AWG is used for OMUX, the arrangement is reverse to the arrangement in case AWG is used for ODMX. OADM is provided with plural 2 x 2 SWs and can extract plural optical signals or can add them. In Japanese published unexamined patent application No. Hei 11-202152, OADM provided with two 2 x 2 SWs is disclosed.

[0003] However, in 2 x 2 SW used for well-known OADM, two 2-input/1-output optical switches (hereinafter called 2 x 1 SW) are arranged so that the respective one output terminals are opposite and are connected in series. An optical signal of a specific wavelength and an add signal are respectively incident from two input terminals of first 2 x 1 SW and either optical signal is selectively output. The output optical signal is incident on one output terminal of second 2 x 1 SW and is output from either of the two input terminals. However, the configuration of such 2 x 2 SW is complex, compared with that of 2 x 1 SW, is inferior in reliability, and the cost is higher. That is, the consistency of the waveguides of two 2 x 1 SWs is required to be kept, and isolation is required to be enhanced to avoid crosstalk. OADM disclosed in Japanese published unexamined patent application No. Hei 10-511821 and configured so that a signal of each wavelength component is demultiplexed from a wavelength multiplexed optical signal by combining a fiber grating (hereinafter called FBR), light and a circulator is also provided with 2 x 2 SW, and has a problem similar to that described above.

SUMMARY OF THE INVENTION

[0004] Therefore, the present invention provides OADM the reliability of which is high and the cost of which is low; without using 2 x 2 SW. An optical add/drop multiplexer (OADM) according to the invention is provided with an optical demultiplexer (ODMX), a 2 x 1 optical switch and an optical multiplexer (OMUX), and is further provided with an optical coupler that branches a predetermined optical signal of optical signals which an optical demultiplexer demultiplexes from wavelength-multiplexed signal light into first and second branched optical signals. The first branched optical signal branched by the optical coupler and an optical signal to be added to the wavelength-multiplexed signal are incident on the 2 x 1 optical switch, and the switch selectively outputs either optical signal. OMUX multiplexes an optical signal selectively output from the optical switch and optical signals demultiplexed by ODMX except an optical signal incident on the optical coupler. OMUX can multiplex optical signals selectively output from optical switches and optical signals and optical signals demultiplexed by ODMX. Or OMUX can multiplex only an optical signal selectively output from the optical switch. In a concrete example, at least one of ODMX

and OMUX can utilize an arrayed waveguide grating. ODMX can be provided with an optical coupler and an optical band-pass filter for selecting an optical signal of a specific wavelength or can be provided with an optical circulator and a fiber grating for reflecting only an optical signal of a specific wavelength. OADM can be provided with plural optical couplers and plural corresponding 2 x 1 optical switches. Also, OADM can be provided with an optical coupler and a 2 x 1 optical switch for all optical signals demultiplexed from wavelength-multiplexed signal light. This OADM can be provided with a variable optical attenuator and an optical amplifier as means for regulating the level of an optical signal output from the 2 x 1 optical switch. The optical coupler can set the branching ratio so that the second branched optical signal is in a range of the receiving level of a receiver for receiving the second branched optical signal. Such OADM has high reliability and low cost.

BRIEF DESCRIPTION OF THE DRAWINGS

[0005] Preferred features of the present invention will now be described, by way of example only, with reference to the accompanying drawings, in which:-

FIG. 1 is a block diagram showing a conventional-type optical add/drop multiplexer (OADM);

FIGS. 2A and 2B are block diagrams showing an optical add/drop multiplexer (OADM) equivalent to an embodiment of the invention;

FIG. 3 is a block diagram showing an optical add/drop multiplexer (OADM) provided with a variable optical attenuator; and

FIG. 4 is a block diagram showing an optical add/drop multiplexer (OADM) provided with an optical amplifier.

DETAILED DESCRIPTION OF THE PREFERRED EMBODIMENTS

[0006] Referring to FIG. 1, a conventional type optical add/drop multiplexer (OADM) is provided with an optical demultiplexer (ODMX) 11, a 2 x 2 optical switch (2 x 2 SW) 13 and an optical multiplexer (OMUX) 17. ODMX 11 demultiplexes optical signals λ_1 to λ_N respectively having a wavelength of λ_1 , λ_2 , ..., λ_N from a wavelength-multiplexed optical signal 10. The demultiplexed optical signal λ_1 having the wavelength of λ_1 is incident on one of two input terminals of the 2 x 2 SW 13. An add signal 14 added to a wavelength multiplexed signal is incident on the other input terminal of the 2 x 2 SW 13. A through signal (hereinafter called a THR signal) 15, is output from one of two output terminals of the 2 x 2 SW 13 and the THR signal is multiplexed with other demultiplexed optical signals by the OMUX 17. A drop signal 16 can be output from the other output terminal of the 2 x 2 SW 13. Therefore, the 2 x 2 SW 13 can output the add signal 14 as a THR signal or can output the de-

multiplexed optical signal 12, having the wavelength λ_1 as a drop signal 16.

[0007] Referring to FIG. 2A, in an OADM equivalent to the first embodiment of the invention, ODMX 40, an optical coupler 41, 2 x 1 SW 42 and OMUX 43 are cascaded. A wavelength-multiplexed optical signal 44 composed of optical signals of different wavelengths λ_1 to λ_N according to a D-WDM system is incident on ODMX 40. ODMX 40 demultiplexes the wavelength-multiplexed optical signal 44 into N portions of optical signal of wavelengths λ_1 to λ_N . Specific optical signal λ_1 (optical signal of the wavelength λ_1 in an example shown Fig. 2) of the demultiplexed optical signal is incident on the optical coupler 41. The optical coupler 41 branches the incident optical signal λ_1 into two optical signals 48, and 49 according to a branching ratio determined beforehand. One optical signal 48, of these two branched optical signals and the other optical signal 50 are incident from two input terminals of the 2 x 1 SW 42. The 2 x 1 SW 42, a well-known optical switch, selects one of the optical signals input from the two input terminals by applying heat, voltage or magnetism and other means to an optical waveguide and varying the intensity of interference between optical signals of each wavelength or by mechanically switching an optical path, and outputs the selected signal from the output terminal. OMUX 43 multiplexes incident N-portions of optical signals and outputs the result as a wavelength-multiplexed optical signal 47. A well-known arrayed waveguide grating (AWG) for example is used for ODMX 40 and OMUX 43. AWG demultiplexes input wavelength-multiplexed light; however, when the input side and the output side of AWG are reversely installed, AWG multiplexes optical signals of each wavelength and can output wavelength-multiplexed light. ODMX 40 can be configured so that it is provided with an optical coupler for branching a wavelength-multiplexed optical signal by the number of each optical signal and an optical band-pass filter for selecting an optical signal of a specific wavelength of each branched optical signal in addition to AWG described above. Further, ODMX 40 can extract each optical signal by a connecting configuration, including an optical circulator and a fiber grating that reflects only an optical signal of a specific wavelength by the number of optical signal. The two configurations described above are also well-known as AWG.

[0008] The operation of an OADM is as follows. ODMX 40 demultiplexes the wavelength multiplexed optical signal 44 into N portions of optical signals of wavelengths λ_1 to λ_N . In case the optical signal λ_1 of the wavelength λ_1 is a drop signal, the optical coupler 41 is attached to the terminal from which the optical signal λ_1 is output of ODMX 40. The optical coupler 41 branches the optical signal λ_1 into two branched optical signals 48, and 49 of the same wavelength λ_1 according to a branching ratio determined beforehand. The branched optical signal 49 is sent to a receiver as a drop signal. The branching ratio of the optical coupler 41 is

set so that the level of the drop signal 49 is in a range of the receiving level of the receiver that receives this signal. Then, as the level of a signal input to the receiver is not required to be regulated, the receiver can be simplified. Branched optical signal 48₁, as a THR signal output from the optical coupler 41, is incident on one of the two input terminals of 2 x 1 SW 42. Also, an optical signal 50, which is an add signal, is incident on the other input terminal. In a case where 2 x 1 SW 42 is set so that it outputs the optical signal 50 of these two input signals, the optical signal 50 is output from 2 x 1 SW 42 as an add signal, is multiplexed by OMUX 43, and is added to a wavelength-multiplexed optical signal transmitted on an optical-signal transmission line. Also when no add operation is executed, 2 x 1 SW 42 outputs the branched light signal 48₁ (that is, the optical signal 45₁). Therefore, OMUX 43 multiplexes the optical signal 45₁ together with other optical signals and outputs the wavelength-multiplexed optical signal 47. As described above, since the OADM described above is provided with the optical coupler and a 2 x 1 SW in place of a 2 x 2 SW inferior in reliability, the cost can be reduced and the reliability can be enhanced.

[0009] Referring to FIG. 2B, an OADM of a second embodiment is provided with two optical couplers 41 and 51 and two 2 x 1 SWs 42 and 52. For example, when OADM drops an optical signal to plural receivers, such configuration is utilized. FIG. 2B also shows that an optical coupler and a 2 x 1 SW can be respectively arranged from all optical signals comprising a wavelength-multiplexed optical signal. In a case where an optical coupler and a 2 x 1 SW are arranged for all optical signals, the integration of the OADM is facilitated.

[0010] Referring to FIG. 3, an OADM is provided with a variable optical attenuator (hereinafter called a VOA) 60 between 2 x 1 SW 42 AND OMUX 43. VOA 60 can vary the level of an input optical signal so that it is at a predetermined attenuation level. Therefore, the input level of OMUX 43 can be fixed and the output level can be fixed.

[0011] Referring to FIG. 4, an OADM is provided with an optical amplifier 70 between 2 x 1 SW 42 and OMUX 43. A semiconductor optical amplifier or an erbium-doped fiber (hereinafter called EDF) amplifier can be utilized for the optical amplifier 70. The amplification level of the optical amplifier 70 is variable, and the optical amplifier varies the level of an input optical signal according to a set condition so that it is at a predetermined amplification level. The optical amplifier 70 can amplify the level of an input optical signal up to a predetermined level and can fix the input level of OMUX 43.

[0012] As described above, a VOA and the optical amplifier regulate the level of an add signal output from 2 x 1 SW 42. A VOA is installed for some 2 x 1 SWs 42, and the optical amplifier can be installed for the other 2 x 1 SWs 42.

[0013] Since an OADM according to the invention is provided with the optical coupler and a 2 X 1 SW in place

of a 2 X 2 SW inferior in reliability, the cost is low and the reliability is improved. Therefore, it is suitable for an optical communication system according to the D-WDM system.

[0014] While the present invention has been described in connection with certain preferred embodiments, it is to be understood that the subject-matter encompassed by the present invention is not limited to those specific embodiments. On the contrary, it is intended to include all alternatives, modifications and equivalents as can be included within the scope of the following claims.

[0015] Each feature disclosed in this specification (which term includes the claims) and/or shown in the drawings may be incorporated in the invention independently of other disclosed and/or illustrated features.

[0016] The text of the abstract filed herewith is repeated here as part of the specification.

[0017] An optical add/drop multiplexer (OADM) is provided with an optical demultiplexer (ODMX), an optical coupler, a 2-input/1-output optical switch (2 X 1 SW) and an optical multiplexer (OMUX), respectively cascaded. The OADM demultiplexes a wavelength-multiplexed optical signal. The optical coupler branches a demultiplexed optical signal into first and second branched optical signals. The second branched optical signal is a drop signal. The first branched optical signal and an add signal are incident on the 2 X 1 SW. When the add signal is output from the switch, the OMUX multiplexes the add signal and other optical signals, and outputs the result to an optical transmission line as a wavelength-multiplexed optical signal.

Claims

1. An optical add/drop multiplexer provided with an optical demultiplexer, an optical switch and an optical multiplexer, also comprising:

an optical coupler that branches a predetermined optical signal, of optical signals demultiplexed from wavelength-multiplexed signal light by the optical demultiplexer, into first and second branched optical signals;

wherein:

the optical switch is a 2-input/1-output optical switch, the first branched optical signal and an optical signal to be added to the wavelength-multiplexed signal are incident on the optical switch, and the optical switch selectively outputs either optical signal.

2. An optical add/drop multiplexer according to Claim 1, further comprising:

one or more additional optical couplers; and,
a corresponding number of additional 2-input/

1-output optical switches, each respectively connecting to one of the additional optical couplers;
 wherein:
 optical signals of different wavelengths are incident on each optical coupler.

3. An optical add/drop multiplexer according to Claim 2, wherein:
 optical couplers and 2-input/1-output optical switches are respectively arranged for all optical signals demultiplexed from wavelength-multiplexed signal light. 5
4. An optical add/drop multiplexer according to Claim 1, wherein:
 the optical multiplexer multiplexes the optical signal selectively output from the optical switch and optical signals demultiplexed by the optical demultiplexer except the predetermined optical signal. 10 15 20
5. An optical add/drop multiplexer according to Claim 1 or 2, wherein:
 the optical multiplexer multiplexes optical signals selectively output from the 2-input/1-output optical switch and optical signals demultiplexed by the optical demultiplexer. 25
6. An optical add/drop multiplexer according to Claim 3, wherein:
 an optical multiplexer multiplexes optical signals selectively output from a 2-input/1-output optical switch. 30
7. An optical add/drop multiplexer according to Claim 1, further comprising:
 means for regulating the level of an optical signal output from a 2-input/1-output optical switch. 35
8. An optical add/drop multiplexer according to Claim 7, wherein:
 the means for regulating the level of an optical signal output is a variable optical attenuator. 40
9. An optical add/drop multiplexer according to Claim 7, wherein:
 the means for regulating the level of an optical signal output is an optical amplifier. 45
10. An optical add/drop multiplexer according to Claim 1, wherein:
 the branching ratio of an optical coupler is set so that a second branched optical signal is in a range of the receiving level of a receiver that receives the optical signal. 50 55
11. An optical add/drop multiplexer according to Claim 1, wherein:

at least one of the demultiplexer and the multiplexer is an arrayed waveguide grating.

12. An optical add/drop multiplexer according to Claim 1, wherein:
 an optical demultiplexer is provided with an optical coupler and an optical band-pass filter that selects an optical signal of a specific wavelength.
13. An optical add/drop multiplexer according to Claim 1, wherein:
 an optical demultiplexer is provided with an optical circulator and a fiber grating that reflects only an optical signal of a specific wavelength.




FIG.1
PRIOR ART




FIG.2A




FIG.2B




FIG.3





FIG.4



Europäisches Patentamt
European Patent Office
Office européen des brevets



(11) EP 1 096 713 A3

(12) EUROPEAN PATENT APPLICATION

(88) Date of publication A3:
11.09.2002 Bulletin 2002/37

(51) Int Cl.7: H04J 14/02

(43) Date of publication A2:
02.05.2001 Bulletin 2001/18

(21) Application number: 00309452.1

(22) Date of filing: 26.10.2000

(84) Designated Contracting States:
AT BE CH CY DE DK ES FI FR GB GR IE IT LI LU
MC NL PT SE
Designated Extension States:
AL LT LV MK RO SI

(72) Inventors:
• Yoshizawa, Nobukazu
Minato-ku, Tokyo (JP)
• Iwano, Tadayuki, c/o NEC Corporation
Tokyo (JP)

(30) Priority: 26.10.1999 JP 30328099

(71) Applicant: NEC CORPORATION
Tokyo (JP)

(74) Representative: Molr, Michael Christopher et al
Mathys & Squire
100 Gray's Inn Road
London WC1X 8AL (GB)

(54) Optical add/drop multiplexer

(57) An optical add/drop multiplexer (OADM) is provided with an optical demultiplexer (ODMX), an optical coupler, a 2-input/1-output optical switch (2 X 1 SW) and an optical multiplexer (OMUX), respectively cascaded. The OADM demultiplexes a wavelength-multiplexed optical signal. The optical coupler branches a demultiplexed optical signal into first and second branched op-

tical signals. The second branched optical signal is a drop signal. The first branched optical signal and an add signal are incident on the 2 X 1 SW. When the add signal is output from the switch, the OMUX multiplexes the add signal and other optical signals, and outputs the result to an optical transmission line as a wavelength-multiplexed optical signal.




FIG.2A

EP 1 096 713 A3



European Patent
Office

EUROPEAN SEARCH REPORT

Application Number
EP 00 30 9452

DOCUMENTS CONSIDERED TO BE RELEVANT			
Category	Citation of document with indication, where appropriate, of relevant passages	Relevant to claim	CLASSIFICATION OF THE APPLICATION (Int.Cl.7)
X	DE 43 37 089 A (SIEMENS AG) 4 May 1995 (1995-05-04)	1-6, 10-13	H04J14/02
Y	* column 1, line 3 - line 33 * * column 3, line 55 - column 4, line 39 *	7-9	
P, X	WO 99 60740 A (LAHAT AMIR ; SFADYA YAKOV (IL); 3COM CORP (US)) 25 November 1999 (1999-11-25) * page 1, line 3 - line 5 * * page 10, line 6 - page 11, line 3 * * page 17, line 20 - page 20, line 8; figure 6 *	1-6, 10	
Y	"SIMULATION OF ASE NOISE ACCUMULATION IN A WAVELENGTH ADD-DROP MULTIPLEXER CASCADE" IEEE PHOTONICS TECHNOLOGY LETTERS, IEEE INC. NEW YORK, US, vol. 9, no. 9, September 1997 (1997-09), pages 1274-1276, XP000924905 ISSN: 1041-1135 * page 1274, left-hand column, paragraph 1 - right-hand column, paragraph 1; figure 1 * * page 1275, left-hand column, paragraph 2 - page 1276, right-hand column, paragraph 1 * --- -/-	7-9	
The present search report has been drawn up for all claims			TECHNICAL FIELDS SEARCHED (Int.Cl.7) H04J
Place of search THE HAGUE		Date of completion of the search 18 July 2002	Examiner Roldán Andrade, J
<p>CATEGORY OF CITED DOCUMENTS</p> <p>X : particularly relevant if taken alone Y : particularly relevant if combined with another document of the same category A : technological background O : non-written disclosure P : intermediate document</p> <p>T : theory or principle underlying the invention E : earlier patent document, but published on, or after the filing date D : document cited in the application L : document cited for other reasons Δ : member of the same patent family, corresponding document</p>			

EPO FORM 1501 (03.02) (P/COD)



European Patent
Office

EUROPEAN SEARCH REPORT

Application Number
EP 00 30 9452

DOCUMENTS CONSIDERED TO BE RELEVANT			
Category	Citation of document with indication, where appropriate, of relevant passages	Relevant to claim	CLASSIFICATION OF THE APPLICATION (Int.Cl.7)
A	<p>SHEHADEH F ET AL: "GAIN-EQUALIZED EIGHT-WAVELENGTH WDM OPTICAL ADD-DROP MULTIPLEXER WITH 8-DB DYNAMIC RANGE" OPTICAL FIBER COMMUNICATION. SUMMARIES OF PAPERS PRESENTED AT THE CONFERENCE OFC '95. SAN DIEGO, FEB. 26 - MAR. 3, 1995, NEW YORK, IEEE, US, 26 February 1995 (1995-02-26), pages 29-30, XP000517633 ISBN: 0-7803-2654-7</p> <p>* page 29, left-hand column, paragraph 1 - right-hand column, paragraph 1; figure 1 *</p>	11-13	
			TECHNICAL FIELDS SEARCHED (Int.Cl.7)
The present search report has been drawn up for all claims			
Place of search THE HAGUE		Date of completion of the search 18 July 2002	Examiner Roldán Andrade, J
<p>CATEGORY OF CITED DOCUMENTS</p> <p>X : particularly relevant if taken alone Y : particularly relevant if combined with another document of the same category A : technological background O : non-written disclosure P : intermediate document</p> <p>T : theory or principle underlying the invention E : earlier patent document, but published on, or after the filing date D : document cited in the application L : document cited for other reasons & : member of the same patent family, corresponding document</p>			

EP0 FORM 1503 03 02 (P04001)

**ANNEX TO THE EUROPEAN SEARCH REPORT
ON EUROPEAN PATENT APPLICATION NO.**

EP 00 30 9452

This annex lists the patent family members relating to the patent documents cited in the above-mentioned European search report. The members are as contained in the European Patent Office EDP file on
The European Patent Office is in no way liable for these particulars which are merely given for the purpose of information.

18-07-2002

Patent document cited in search report		Publication date	Patent family member(s)		Publication date
DE 4337089	A	04-05-1995	DE	4337089 A1	04-05-1995
WO 9960740	A	25-11-1999	US	6233074 B1	15-05-2001
			AU	3118999 A	06-12-1999
			WO	9960740 A1	25-11-1999

EPO FORM P0459

For more details about this annex : see Official Journal of the European Patent Office, No. 12/82